


CE10-0R640T

Elite 0.6-40 GHz Directional Coupler

DEVICE OVERVIEW

General Description

The CE10-0R640 is a next generation broadband 600MHz to 40GHz, 10dB directional coupler from the Marki Elite Series. Conductive paint is applied to all Elite Series products to reduce EMI/RFI leakage and susceptibility. The CE10-0R640 offers the best directivity, return loss, and coupling accuracy available on the market. Available as both a three port directional coupler and a four port bidirectional coupler, the CE10-0R640 is an exceptional choice for broadband return loss measurements, power leveling, and signal monitoring applications. Sophisticated neural network design techniques combined with deep circuit knowledge and triplate stripline construction allow the Marki Elite Series of Couplers to provide superior performance to all other directional couplers available.



[Download s-parameters here](#)


Features

- Broadband Performance
- Excellent Coupling Flatness
- High Directivity
- Low VSWR
- Conductive paint minimizes RF leakage

Applications

N/A

Functional Block Diagram



Part Ordering Options

Part Number	Description	Package	Packing Size	Green Status	Product Lifecycle	Export Classification
CE10-0R640	Elite 0.6-40 GHz Directional Coupler	-	-	RoHS	Released	EAR99
CE10-0R640T	Elite 0.6-40 GHz Directional Coupler	-	-	RoHS	Released	EAR99

Table Of Contents

■ Device Overview

- General Description
- Features
- Applications
- Functional Block Diagram

■ Port Configuration and Functions

- Port Diagram
- Port Functions

■ Specifications

- Absolute Maximum Ratings
- Package Information
- Electrical Specifications
- Typical Performance Plots
- Performance Over Temperature
- Terminated Return Loss and Directivity

Port Configuration and Functions



Port Diagram

A side view of the CE10-0R640 package outline drawing is shown below. The CE10-0R640 has input and output ports given in Port Functions. The CE10-0R640 can be used in either the forward or reverse direction corresponding to configuration A and B respectively. For configuration A, input signal into port 1, use port 3 for coupled port, port 2 for isolated port, and port 4 for output port. For configuration B, input signal into port 4, use port 2 for coupled port, port 3 for isolated port, and port 1 for output port.






Port Functions

Configuration A

Port	Function	Description	Equivalent Circuit for Package
Port 1	Input	The input port is DC short to the output port and open to the isolated and coupled ports.	
Port 2	Isolated	The isolated port is DC short to the coupled port and open to the input and output ports.	
Port 3	Coupled	The coupled port is DC short to the isolated port and open to the input and output ports.	
Port 4	Output	The output port is DC short to the input port and open to the isolated and coupled ports.	

Configuration B

Port	Function	Description	Equivalent Circuit for Package
Port 1	Output	The input port is DC short to the output port and open to the isolated and coupled ports.	
Port 2	Coupled	The isolated port is DC short to the coupled port and open to the input and output ports.	
Port 3	Isolated	The coupled port is DC short to the isolated port and open to the input and output ports.	
Port 4	Input	The output port is DC short to the input port and open to the isolated and coupled ports.	

Specifications

Absolute Maximum Ratings

The Absolute Maximum Ratings indicate limits beyond which damage may occur to the device. If these limits are exceeded, the device may be inoperable or have a reduced lifetime.

Parameter	Maximum Rating	Unit
RF Power Handling	20	W

Package Information

Parameter	Details	Rating
Dimensions	-	110.5 x 17.5 mm

Electrical Specifications

The electrical specifications apply for configuration A at TA=+25°C in a 50Ω system. Min and Max limits are guaranteed at TA=+25°C.

Parameter	Port Configuration	Test Conditions	Minimum Frequency (GHz)	Maximum Frequency (GHz)	Min	Typ	Max	Unit
Mean Coupling	-	-	0.6	40	9.5	10	10.5	dB
Coupling Loss ¹	-	-	0.6	40	0.41	0.46	0.52	dB
Direct Line Insertion Loss	-	DC-40	-	-	-	1.3	2.3	dB
Amplitude Flatness ²	-	-	0.6	40	-	0.2	0.5	dB
Maximum Coupling Deviation	-	-	0.6	40	-	0.8	1.5	dB
Directivity	-	-	0.6	40	15	20	-	dB
IL Corrected Directivity ³	-	-	0.6	40	16	24	-	dB
Excess Insertion Loss (dB) ⁴	-	DC-40	-	-	-	0.85	1.8	dB
Impedance	-	-	-	-	-	50	-	Ω
Pass Band Return Loss	-	DC-40	-	-	19	30	-	dB
Pass Band VSWR	-	DC-40	-	-	-	1.07	1.25	-

^[1] Coupling loss based on average coupling factor.






^[2] Amplitude Flatness = Median value of ABS(Measured Coupling Power – Average Coupling Factor).

^[3] IL Corrected Directivity = Directivity + Insertion Loss.





^[4] Excess Insertion Loss = (Input Port to Output Port Insertion Loss) – Coupling Loss.

Typical Performance Plots



Insertion Loss, Return Loss, Coupled Port Power, and Directivity



Performance Over Temperature



Terminated Return Loss and Directivity



DISCLAIMER

MARKI MICROWAVE, INC., ("MARKI") PROVIDES TECHNICAL SPECIFICATIONS AND DATA (INCLUDING DATASHEETS), APPLICATION OR OTHER DESIGN ADVICE, WEB TOOLS, AND OTHER INFORMATION AND RESOURCES "AS IS" AND WITH ALL FAULTS. MARKI DISCLAIMS ALL WARRANTIES, EXPRESS OR IMPLIED, INCLUDING, WITHOUT LIMITATION, ANY IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE, OR NON-INFRINGEMENT.

These resources are intended for developers skilled in the art designing with Marki products. You are solely responsible for (1) selecting the appropriate products for your application, (2) designing, validating, and testing your application, and (3) ensuring your application meets applicable standards and other requirements. Marki makes no guarantee regarding the suitability of its products for any particular purpose, nor does Marki assume any liability whatsoever arising out of your use or application of any Marki product.

Marki grants you permission to use these resources only for development of an application that uses Marki products. Other reproduction or use of these resources is strictly prohibited. No license is granted to any other Marki intellectual property or to any third-party intellectual property. Marki reserves the right to make changes to the product(s) or information contained herein without notice.

MARKI MICROWAVE and T3 MIXER are trademarks or registered trademarks of Marki Microwave, Inc. All other trademarks used are the property of their respective owners.

© 2021 - 2023, Marki Microwave, Inc