

CE10-1R540T

Elite 1.5-40 GHz Directional Coupler

DEVICE OVERVIEW

General Description

The CE10-1R540 is a next generation broadband 1.5GHz to 40GHz, 10dB directional coupler from the Marki Elite Series. Conductive paint is applied to all Elite Series products to reduce EMI/RFI leakage and susceptibility. The CE10-1R540 offers the best directivity, return loss, and coupling accuracy available on the market. Available as both a three port directional coupler and a four port bidirectional coupler, the CE10-1R540 is an exceptional choice for broadband return loss measurements, power leveling, and signal monitoring applications. Sophisticated neural network design techniques combined with deep circuit knowledge and triplate stripline construction allow the Marki Elite Series of Couplers to provide superior performance to all other directional couplers available.



[Download s-parameters here](#)


Features

- Broadband Performance
- Excellent Coupling Flatness
- High Directivity
- Low VSWR
- Conductive paint minimizes RF leakage

Applications

N/A

Functional Block Diagram



Part Ordering Options

Part Number	Description	Connectors	Green Status	Product Lifecycle	Export Classification
CE10-1R540	Elite 1.5-40 GHz Directional Coupler	Standard	REACH RoHS	Released	EAR99
CE10-1R540T	Elite 1.5-40 GHz Directional Coupler	Standard	REACH RoHS	Released	EAR99

Table Of Contents

- **Device Overview**
 - General Description
 - Features
 - Applications
 - Functional Block Diagram
- **Port Configuration and Functions**
 - Port Diagram
 - Port Functions
- **Revision History**
- **Specifications**
 - Absolute Maximum Ratings
 - Package Information
 - Electrical Specifications
 - Typical Performance Plots
 - Performance Over Temperature
 - Terminated Return Loss and Directivity
- **Mechanical Data**
 - Outline Drawing


Revision History

Revision Code	Revision Date	Comment
-	2021-12-01	Datasheet Initial Release
A	null	Terminated Option Added, Operating and Storage Temperatures Updated




Port Configuration and Functions

Port Diagram

A side view of the CE10-1R540 package outline drawing is shown below. The CE10-1R540 has input and output ports given in Port Functions. The CE10-1R540 can be used in either the forward or reverse direction corresponding to configuration A and B respectively. For configuration A, input signal into port 1, use port 3 for coupled port, and port 4 for output port. Port two is loaded in the CE10-1R540T and the device can only be used in configuration A.



Port Functions

Port	Function	Connector Type	Description	Equivalent Circuit for Package
Port 1	Input	2.92F	The input port is DC short to the output port and open to the isolated and coupled ports.	
Port 2	Isolated	2.92F	The isolated port is DC short to the coupled port and open to the input and output ports. This port has a factory installed 50 Ohm termination.	
Port 3	Coupled	2.92F	The coupled port is DC short to the isolated port and open to the input and output ports.	
Port 4	Output	2.92F	The output port is DC short to the input port and open to the isolated and coupled ports.	

Specifications

Absolute Maximum Ratings

The Absolute Maximum Ratings indicate limits beyond which damage may occur to the device. If these limits are exceeded, the device may be inoperable or have a reduced lifetime.

Parameter	Maximum Rating	Unit
RF Power Handling	20	W

Package Information

Parameter	Details	Rating
Dimensions	-	68.62 x 17.53 mm

Electrical Specifications

The electrical specifications apply for configuration A at TA=+25°C in a 50Ω system. Min and Max limits are guaranteed at TA=+25°C.

Parameter	Test Conditions	Minimum Frequency (GHz)	Maximum Frequency (GHz)	Min	Typ	Max	Unit
Mean Coupling	-	1.5	40	9.5	10	10.5	dB
Coupling Loss ¹	-	1.5	40	0.41	0.46	0.52	dB
Direct Line Insertion Loss	DC-40	-	-	-	0.9	1.7	dB
Amplitude Flatness ²	-	1.5	40	-	0.25	0.5	dB
Maximum Coupling Deviation	-	1.5	40	-	0.85	1.7	dB
Directivity	-	1.5	40	15	20	-	dB
IL Corrected Directivity ³	-	1.5	40	16	22	-	dB
Excess Insertion Loss (dB) ⁴	DC-40	-	-	-	0.42	1.3	dB
Impedance	-	-	-	-	50	-	Ω
Passband Return Loss	DC-40	-	-	19	30	-	dB
Pass Band VSWR	DC-40	-	-	-	1.07	1.25	-

^[1] Coupling loss based on average coupling factor






^[2] Amplitude Flatness = Median value of ABS(Measured Coupling Power – Average Coupling Factor).

^[3] IL Corrected Directivity = Directivity + Insertion Loss.



^[4] Excess Insertion Loss = (Input Port to Output Port Insertion Loss) – Coupling Loss.

Typical Performance Plots

Insertion Loss, Return Loss, Coupled Port Power, and Directivity





Performance Over Temperature





CE10-1R540T

Elite 1.5-40 GHz Directional Coupler



Terminated Return Loss and Directivity




CE10-1R540T

Elite 1.5-40 GHz Directional Coupler

Mechanical Data

Outline Drawing



DISCLAIMER

MARKI MICROWAVE, INC., ("MARKI") PROVIDES TECHNICAL SPECIFICATIONS AND DATA (INCLUDING DATASHEETS), APPLICATION OR OTHER DESIGN ADVICE, WEB TOOLS, AND OTHER INFORMATION AND RESOURCES "AS IS" AND WITH ALL FAULTS. MARKI DISCLAIMS ALL WARRANTIES, EXPRESS OR IMPLIED, INCLUDING, WITHOUT LIMITATION, ANY IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE, OR NON-INFRINGEMENT.

These resources are intended for developers skilled in the art designing with Marki products. You are solely responsible for (1) selecting the appropriate products for your application, (2) designing, validating, and testing your application, and (3) ensuring your application meets applicable standards and other requirements. Marki makes no guarantee regarding the suitability of its products for any particular purpose, nor does Marki assume any liability whatsoever arising out of your use or application of any Marki product.

Marki grants you permission to use these resources only for development of an application that uses Marki products. Other reproduction or use of these resources is strictly prohibited. No license is granted to any other Marki intellectual property or to any third-party intellectual property. Marki reserves the right to make changes to the product(s) or information contained herein without notice.

MARKI MICROWAVE and T3 MIXER are trademarks or registered trademarks of Marki Microwave, Inc. All other trademarks used are the property of their respective owners.

© 2021, Marki Microwave, Inc