

MM1-0312SCH-2

GaAs MMIC Double Balanced Mixer

DEVICE OVERVIEW

General Description

The MM1-0312S is a passive double balanced MMIC mixer. It features excellent conversion loss, superior isolations and spurious performance across a broad bandwidth, in a highly miniaturized form factor. Accurate, nonlinear simulation models are available for Microwave Office® through the Marki Microwave PDK. The MM1-0312S is available as a wire bondable chip or an SMA connectorized package. The MM1-0312S is a superior alternative to Marki Microwave carrier and packaged M1 and M3 mixers.




Features

- Compact Chip Style Package (0.054" x 0.046"x0.004")
- CAD Optimized for Superior Isolation and Spurious Response
- Broadband Performance
- Excellent Unit-to-Unit Repeatability
- Fully nonlinear software models available with Marki PDK for Microwave Office®
- RoHS Compliant

Applications

N/A

Functional Block Diagram



Part Ordering Options

Part Number	Description	Package	Packing Size	Green Status	Product Lifecycle	Export Classification
MM1-0312SCH-2	GaAs MMIC Double Balanced Mixer	CH	-	RoHS	Released	EAR99
<u>MM1-0312SS</u>	GaAs MMIC Double Balanced Mixer	S	-	RoHS	Released	EAR99

Table Of Contents


■ Device Overview	■ Specifications
General Description	Absolute Maximum Ratings
Features	Package Information
Applications	Recommended Operating Conditions
Functional Block Diagram	Electrical Specifications
	Typical Performance
	Spur Tables
■ Port Configuration and Functions	■ Die Mounting Recommendations
Port Diagram	Mounting and Bounding Recommendations
Port Functions	
■ Revision History	■ Mechanical Data
	Outline Drawing
	■ Notes

Revision History

Revision Code	Revision Date	Comment
A	2017-08-01	Die shrunk from 1.48 x 1.18 mm ² to 1.37 x 1.17 mm ² . CH package tolerance added.
B	2020-01-01	Updated CH package Outline Dimensions


Port Configuration and Functions

Port Diagram





Port Functions

Configuration A

Port	Function	Description	Equivalent Circuit for Package
Port 1	LO	Port 1 is DC short and AC matched to 50 Ω from 3 to 12 GHz. Blocking capacitor is optional.	
Port 2	IF	Port 2 is DC coupled to the diodes. Blocking capacitor is optional.	
Port 3	RF	Port 3 is DC short and AC matched to 50 Ω from 3 to 12 GHz. Blocking capacitor is optional.	

Configuration B

Port	Function	Description	Equivalent Circuit for Package
Port 1	RF	Port 1 is DC short and AC matched to 50 Ω from 3 to 12 GHz. Blocking capacitor is optional.	
Port 2	IF	Port 2 is DC coupled to the diodes. Blocking capacitor is optional.	
Port 3	LO	Port 3 is DC short and AC matched to 50 Ω from 3 to 12 GHz. Blocking capacitor is optional.	

Specifications

Absolute Maximum Ratings

Parameter	Maximum Rating	Unit
Maximum Operating Temperature	100	°C
Maximum Storage Temperature	125	°C
Minimum Operating Temperature	-55	°C
Minimum Storage Temperature	-65	°C
Port 2 DC Current	50	mA
RF Power Handling (RF+LO), 100°C	20	dBm
RF Power Handling (RF+LO), 25°C	25	dBm

Package Information

Parameter	Details	Rating
Dimensions	-	1.37 x 1.17 mm

Recommended Operating Conditions







Parameter	Min	Nominal	Max	Unit
LO Input Power	17	-	23	dBm







Electrical Specifications







Specifications guaranteed from -55 to +100°C, measured in a 50Ω system. All bare die are 100% DC tested and 100% visually inspected. RF testing is performed on a sample basis to verify conformance to datasheet guaranteed specifications. Consult factory for more information.

Parameter	Port Configuration	Test Conditions	Min	Typ	Max	Unit
RF Frequency Range	-	-	3	-	12	GHz
LO Frequency Range	-	-	3	-	12	GHz
Conversion Loss	A	LO/RF=3-12 GHz IF=DC-4.5 GHz LO Drive Level=20dBm	-	7.5	-	dB
Conversion Loss	B	LO/RF=3-12 GHz IF=DC-4.5 GHz LO Drive Level=20dBm	-	9	-	dB
Isolation, LO to RF	-	LO/RF=3-12 GHz IF=DC-4.5 GHz LO Drive Level=18-23dBm	-	47	-	dB
Isolation, LO to IF	-	LO/RF=3-12 GHz IF=DC-4.5 GHz LO Drive Level=18-23dBm	-	31	-	dB
Isolation, RF to IF	-	LO/RF=3-12 GHz IF=DC-4.5 GHz LO Drive Level=18-23dBm	-	36	-	dB
Input IP3	A	LO/RF=3-12 GHz IF=DC-4.5 GHz LO Drive Level=18-23dBm	-	24	-	dBm
Input IP3	B	LO/RF=3-12 GHz IF=DC-4.5 GHz LO Drive Level=18-23dBm	-	26	-	dBm
IF Frequency Range	-	-	0	-	4.5	GHz
Input 1dB Compression	A	LO/RF=3-12 GHz IF=DC-4.5 GHz LO Drive Level=18-23dBm	-	14	-	dBm
Input 1dB Compression	B	LO/RF=3-12 GHz IF=DC-4.5 GHz LO Drive Level=18-23dBm	-	14	-	dBm

Typical Performance







Spur Table

Downconversion Spurious Suppression

Spurious data is taken by selecting RF and LO frequencies (+mLO+nRF) within the 3 to 12 GHz RF/LO bands, which create a 91 MHz IF spurious output. The mixer is swept across the full spurious band and the mean is calculated. The numbers shown in the table below are for a -10 dBm RF input. Spurious suppression is scaled for different RF power levels by (n-1), where “n” is the RF spur order. For example, the 2RFx2LO spur is 82 dBc for the A configuration for a -10 dBm input, so a -20 dBm RF input creates a spur that is (2-1) x (-10 dB) dB lower, or 92 dBc.

Typical Downconversion Spurious Suppression (dBc): A Configuration (B Configuration), Sine Wave LO ⁵

-10 dBm RF Input	0xLO	1xLO	2xLO	3xLO	4xLO	5xLO
1xRF	29 (20)	Reference	33 (47)	17 (15)	35 (45)	N/A
2xRF	72 (75)	67 (60)	82 (85)	76 (64)	82 (91)	75 (74)
3xRF	79 (75)	72 (76)	96 (98)	80 (86)	88 (99)	74 (80)
4xRF	N/A	120 (118)	123 (121)	117 (118)	121 (121)	124 (120)
5xRF	N/A	135 (134)	136 (136)	131 (132)	135 (136)	128 (128)

Specifications are subject to change without notice. Contact Marki Microwave for the most recent specifications and data sheets.

Upconversion Spurious Suppression

Spurious data is taken by mixing a 91 MHz IF with LO frequencies (+mLO+nIF), which creates an RF within the 3 to 12 GHz RF band. The mixer is swept across the full spurious output band and the mean is calculated. The numbers shown in the table below are for a -10 dBm IF input. Spurious suppression is scaled for different IF input power levels by (n-1), where “n” is the IF spur order. For example, the 2IFx1LO spur is typically 79 dBc for the A configuration for a -10 dBm input, so a -20 dBm IF input creates a spur that is (2-1) x (-10 dB) dB lower, or 89 dBc.

Typical Upconversion Spurious Suppression (dBc): A Configuration (B Configuration), Sine Wave LO ⁵

-10 dBm RF Input	0xLO	1xLO	2xLO	3xLO	4xLO	5xLO
1xIF	26 (26)	Reference	36 (42)	13 (12)	35 (46)	21 (23)
2xIF	68 (61)	79 (80)	73 (63)	76 (81)	76 (67)	79 (85)
3xIF	86 (93)	80 (81)	89 (98)	79 (79)	89 (97)	78 (81)
4xIF	114 (102)	122 (123)	119 (114)	127 (126)	125 (115)	124 (124)
5xIF	120 (134)	131 (133)	137 (136)	132 (136)	137 (136)	132 (130)

Specifications are subject to change without notice. Contact Marki Microwave for the most recent specifications and data sheets.

Die Mounting Recommendations

Mounting and Bonding Recommendations

Marki MMICs should be attached directly to a ground plane with conductive epoxy. The ground plane electrical impedance should be as low as practically possible. This will prevent resonances and permit the best possible electrical performance. Datasheet performance is only guaranteed in an environment with a low electrical impedance ground.

Mounting - To epoxy the chip, apply a minimum amount of conductive epoxy to the mounting surface so that a thin epoxy fillet is observed around the perimeter of the chip. Cure epoxy according to manufacturer instructions.

Wire Bonding - Ball or wedge bond with 0.025 mm (1 mil) diameter pure gold wire. Thermosonic wirebonding with a nominal stage temperature of 150 °C and a ball bonding force of 40 to 50 grams or wedge bonding force of 18 to 22 grams is recommended. Use the minimum level of ultrasonic energy to achieve reliable wirebonds. Wirebonds should be started on the chip and terminated on the package or substrate. All bonds should be as short as possible <0.31 mm (12 mils).

Circuit Considerations – 50 Ω transmission lines should be used for all high frequency connections in and out of the chip. Wirebonds should be kept as short as possible, with multiple wirebonds recommended for higher frequency connections to reduce parasitic inductance. In circumstances where the chip more than .001" thinner than the substrate, a heat spreading spacer tab is optional to further reduce bondwire length and parasitic inductance.


Handling Precautions

General Handling: Chips should be handled with care using tweezers or a vacuum collet. Users should take precautions to protect chips from direct human contact that can deposit contaminants, like perspiration and skin oils on any of the chip's surfaces.

Static Sensitivity: GaAs MMIC devices are subject to static discharge, and should be handled, assembled, tested, and transported only in static protected environments.


Cleaning and Storage: Do not attempt to clean the chip with a liquid cleaning system or expose the bare chips to liquid. Once the ESD sensitive bags the chips are stored in are opened, chips should be stored in a dry nitrogen atmosphere.

Bonding Diagram



Mechanical Data

Outline Drawing



Notes

1. Mixer Conversion Loss Plot IF frequency is 100 MHz.
2. Mixer Noise Figure typically measures within 0.5 dB of conversion loss for IF frequencies greater than 5 MHz.
3. Conversion Loss typically degrades less than 0.5 dB at +100°C and improves less than 0.5 dB at -55°C.
4. Unless otherwise specified, data is taken with +20 dBm lowside LO drive.
5. Specifications are subject to change without notice. Contact Marki Microwave for the most recent specifications and data sheets.
6. Catalog mixer circuits are continually improved. Configuration control requires custom mixer model numbers and specifications.

Note: Exposure to maximum rating conditions for extended periods may reduce device reliability. There is no damage to device with only one parameter set at the limit and all other parameters set at or below their nominal value. Exceeding any of the limits listed here may result in permanent damage to the device.

DISCLAIMER

MARKI MICROWAVE, INC., ("MARKI") PROVIDES TECHNICAL SPECIFICATIONS AND DATA (INCLUDING DATASHEETS), APPLICATION OR OTHER DESIGN ADVICE, WEB TOOLS, AND OTHER INFORMATION AND RESOURCES "AS IS" AND WITH ALL FAULTS. MARKI DISCLAIMS ALL WARRANTIES, EXPRESS OR IMPLIED, INCLUDING, WITHOUT LIMITATION, ANY IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE, OR NON-INFRINGEMENT.

These resources are intended for developers skilled in the art designing with Marki products. You are solely responsible for (1) selecting the appropriate products for your application, (2) designing, validating, and testing your application, and (3) ensuring your application meets applicable standards and other requirements. Marki makes no guarantee regarding the suitability of its products for any particular purpose, nor does Marki assume any liability whatsoever arising out of your use or application of any Marki product.

Marki grants you permission to use these resources only for development of an application that uses Marki products. Other reproduction or use of these resources is strictly prohibited. No license is granted to any other Marki intellectual property or to any third-party intellectual property. Marki reserves the right to make changes to the product(s) or information contained herein without notice.

MARKI MICROWAVE and T3 MIXER are trademarks or registered trademarks of Marki Microwave, Inc. All other trademarks used are the property of their respective owners.

© 2017, 2020, Marki Microwave, Inc