

Handoff Receivers for E3238S

Currently supported hand-off receivers for the E3238S - Blackbird System									A.02.00/B.02.00		
Hand-off Receiver	Description	Tuning Resolution in Hz	Frequency Range	Bandwidths	Modulation Detection Types	Noise Figure in dB	2nd Order IM	3rd Order IM	Form Factor & Interface	Auto Gain Ctrl	Beat Frequency Oscillator
WJ-8607	Mini-Ceptor	100	2MHz - 512 MHz 2MHz - 2 GHz	10,20,100KHz, 1,3,12MHz	AM,FM,CW, USB,LSB,Pulse				External RS-235	Yes	+/-4000Hz
WJ-8611	Digital UHF/VHF Receiver	10	20MHz - 1GHz	200Hz - 200KHz (15 steps)	AM,FM,CW, USB,LSB	12	40	40	External RS-232	Yes	+/-8000Hz
WJ-8615P											
WJ-8629	Digital UHF/VHF Receiver										
WJ-8711	Digital HF Receiver	1	5KHz - 30MHz	56Hz - 16KHz (66 Steps)	AM,FM,CW, USB,LSB	14	60	30	External RS-232	Yes	+/-8000Hz
WJ-8712	Digital HF Receiver	1	5KHz - 30MHz	56Hz - 16KHz (66 Steps)	AM,FM,CW, USB,LSB	14	60	30	External RS-232	Yes	+/-8000Hz
WJ-8712P	Digital HF Receiver	1	5KHz - 30MHz	56Hz - 16KHz (66 Steps)	AM,FM,CW, USB,LSB	14	60	30	External RS-232	Yes	+/-8000Hz
WJ-8721	Digital HF Receiver	1	5KHz - 30MHz	56Hz - 16KHz (66 Steps)	AM,FM,CW, USB,LSB,ISB	14	60	30	VXI	Yes	+/-8000Hz
Cubic R-3250	Digital HF Receiver	1	10KHz - 30MHz	100Hz - 16KHz (51 Steps)	AM,FM,CW, USB,LSB,ISB	15	60	30	VXI	Yes	+/-8000Hz
Cubic R-3550	Digital UHF/VHF Receiver	10	20 - 1200MHz	1KHz - 240KHz (17 Steps)	AM,FM,CW, USB,LSB	12	60	14	VXI	Yes	+/-8000Hz
Software											
HP-89441											
<p><i>The above specifications are for comparison purposes only.</i></p> <p><i>The specifications may vary at different bandwidths, frequencies or amplitudes.</i></p> <p><i>For more detailed specifications contact the manufacture listed below:</i></p>											
Company	Contact Name		Phone	FAX	E-Mail						
Wakins Johnson	H. Bradford Wynne		619-460-4205	619-460-2535	brad.wynne@wj.com						
	Mark E. Garland		301-948-7550 Ext:7333								
Cubic	Dr. Clive Winkler		619-643-5837	619-643-5803	clive.winkler@cubic.com						